



Uninterruptible power supply ACUPS-01



2nd generation valves (Wi-Fi and Zigbee)



Sedna Mesh valves (Wi-Fi and Zigbee)



Control4 Zigbee valve



Sinopé Zigbee gateway



Sinopé Mesh gateway

*The UPS does not replace the 4 backup batteries of the Sedna valve. Backup batteries are necessary if you want the valve to close (depending on the function selected in Neviweb or Sinopé Smart Systems) during a prolonged power outage of more than 24 hours.

■ FEATURES

- Self-rechargeable battery backup in case of power failure
- Adjusts the output voltage according to the voltage of the device to which it is connected, when the power supply is cut off

■ STANDARDS

Complies with EN62040-2:2006

Complies with EN6100-3-2-2006+A12009+A2:2009

Complies with EN6100-3-3:2008

■ TECHNICAL SPECIFICATIONS

Operation: 32 °F to 104 °F [0 °C to 40 °C]

Storage: -4 °F to 122 °F [-20 °C to 50 °C]

Supply:

Input: DC 5 V / 7.5 V / 9 V /12 V

Output: DC 5 V / 7.5 V / 9 V /12 V

Output power: 12 W

Battery voltage: DC 3.7 V 18.5 Wh

Battery:

Type: Lithium-ion

Recharging time of the battery: Between 8 hours [12 V] and 12 hours [5 V] depending on the voltage.

Battery life* : 24 hours [with the valve] and 16 hours [with the gateway]

Maximum number of cycles : 400

3-year warranty

Indoor use only.

*If the battery is 100% charged

